

## How to change the parameters of the AED Trainer 3 configuration software

(If you want to upgrade the software on the AED Trainer 3 to the latest version, please see separate how to document)

The steps below provide supplementary guidance to the AED Trainer 3 Direction for Use on how to update the AED Trainer 3 parameter settings using the configuration software from the AED Trainer Operating System (SD) Card.

1) Insert the Operating System card into the Card Slot of your Computer or if no slot is available , install the card into a standard card reader and connect it to your computer

2) Double click onto Aedt3Cfg.exe file:

so 🕨 Compu	ıter ► SD (D:) ►	the first state of the second state of the sec	
🔹 🖻 Ope	en New folder		
rites	Name	Date modified	Туре
sktop	🐌 LANG	21.08.2014 09:04	File folder
wnloads	🐌 LOG_5019.CPR	31.12.2004 23:00	File folder
opbox	4 LOG_5020.CPR	31.12.2004 23:00	File folder
cent Places	🐌 LOG_5021.CPR	31.12.2004 23:00	File folder
/Drive	4 LOG_5022.CPR	31.12.2004 23:00	File folder
	🐌 LOG_5023.CPR	31.12.2004 23:00	File folder
ries	SYSTEM	21.08.2014 09:04	File folder
ps	Aedt3Cfg	15.10.2013 14:53	Application
cuments	de.mo	26.05.2011 08:41	MO File
isic ≡	📄 du.mo	13.08.2012 09:49	MO File
tures	en.mo	26.05.2011 08:33	MO File
2) Soloct Ion		00 06 2011 22:00	MO Eile

<sup>3)</sup> Select language.

## 4) Click "Open" on the configuration parameter screen that appears shown:

AED Trainer 3 Configuration	×	
AED Protocol Parameters:	CPR Type CPR First Always C Off C On C Set C On	
Shock Series Interval	Adult CPR Duration	
Shock Series	Child CPR Duration	
AED Trainer Parameters:	Manikin LED  Remote Ctrl  Pad Attachment Tolerance    Off  O AEDT3	
Open	Set Defaults Update Exit	

5) Open the Configuration file CONFIG.DAT from the SD Card itself, which is located under files

SYSTEM\CONFIG (step a,b,c)

a:				
Locate and o	oen the AEDT3 Config	guration file		×
Look <u>i</u> n:	🖬 SD (D:)	•	⇔ 🗈 📸 💷 ▼	
Ca	Name	^	Date modified	Туре
Recent Places	퉬 LANG		21.08.2014 09:04	File folder
neceni riaces	🛛 🌡 LOG_5019.CPR		31.12.2004 23:00	File folder
	LOG_5020.CPR		31.12.2004 23:00	File folder
Desktop	LOG_5021.CPR		31.12.2004 23:00	File folder
	LOG_5022.CPR		31.12.2004 23:00	File folder
	LOG_5023.CPR		31.12.2004 23:00	File folder
Libraries	🔒 SYSTEM		21.08.2014 09:04	File folder
Computer				
Network				
	•	III		Þ
	File <u>n</u> ame:		•	<u>O</u> pen
	Files of type:	Aedt3 Config File (CONFIG.DAT)	•	Cancel

## b:

Locate and op	en the AEDT3 Cor	nfiguration file		×
Look <u>i</u> n:	SYSTEM	•	← 🗈 💣 📰 -	
	Name	^	Date modified	Туре
Recent Places	CONFIG		11.04.2014 12:23	File folder
Necenii Flaces	UPDATE		11.04.2014 12:23	File folder
Desktop				
Libraries				
Computer				
Network				
	•			+
	File <u>n</u> ame:		•	<u>O</u> pen
	Files of type:	Aedt3 Config File (CONFIG.DAT)	•	Cancel

c:						
1	Locate and op	en the AEDT3 Co	nfiguration file			×
	Look in:	\rm CONFIG		•	← 🗈 💣 📰 ▾	
	C	Name	*		Date modified	Туре
	Recent Places	CONFIG.DA	Γ		21.08.2014 09:31	DAT File
	Desktop					
	Libraries					
	Computer					
1						
	Network					
		•	III			•
		File <u>n</u> ame:	CONFIG		•	<u>O</u> pen
		Files of type:	Aedt3 Config File (CONFIG.	DAT)	-	Cancel

- 6) Adjust the parameter setting as desired.
- 7) After making all the desired changes press "Update"
- 8) Click "Exit" to close the configuration program.
- 9) Eject the SD card from your computer (important!):

📴 🚱 🔽 👝 Eje	ect Ricoh SD Disk Device SD (D:)
• • •	SD (D:)
0 🕒 🖏 🥏	
Customize	

10) Remove the Operating System Card from the computer or card reader and replace it in the AEDTrainer 3

Ver 2. 2014.08.21